



Approved Meter Equipment Enclosure List:

Revised
3/1/2019

The attached list of self-contained meter sockets and enclosures has been approved for use in the service areas served by the utilities of the Meter Equipment Group. Approval is based on the unit's compliance with the MEG specifications, particularly U.L. listing, sealing requirements, bypass characteristics, and certain operational concerns. The MEG makes no claims regarding nameplate ratings or load side attachments beyond the sealed portion of the meter socket. We recommend that all units be used as intended by the manufacturer. All additional data is supplied for informational purposes only.

NOTES:

- A. All commercial or three phase applications require a unit with an approved bypass device.
(Configuration 3, 4 or 5)
- B. All sockets are listed as their maximum socket amperage. 320/400 Amp enclosures are listed as 400 Amp maximum and 480/600 Amp enclosures are listed as 600 Amp maximum.
- C. Aluminum enclosures are recommended in salt spray areas.
- D. Sealing rings (ring-type sockets) along with all lugs/connectors (line and load side) are considered to be part of the meter enclosure. The customer/contractor is thereby responsible for furnishing these items. Please contact your utility representative to determine the proper size lugs/connectors. The sealing ring must be a captive-screw type equivalent to ABB #01L0028G02, Milbank MR-4/A3068, Landis & Gyr #9738-8002, or Ekstrom 10-9090.
- E. The "configuration" refers to the various meter connecting arrangements used to accommodate the utility meter. These configurations are described below:

SELF CONTAINED CONFIGURATIONS

DESCRIPTION & TYPICAL APPLICATION

1	Residential - 4 Terminal Socket, Single Phase, 3 Wire
2	Residential - 5 Terminal Socket, Network, 3 Wire
3	Residential/Commercial - 4 Terminal Socket (w/Bypass), Single Phase, 3 Wire
3a	Residential/Commercial - 5 Terminal Socket (w/Bypass), Network, 3 Wire
3b	Residential/Commercial - 5 Terminal socket (w/Bypass), Neutral can be isolated for 3-phase, 3-wire applications.
4	Commercial - 7 Terminal Socket (w/Bypass), Three Phase, 4 Wire
*5	Residential/Commercial – K7 Base (w/Bypass), Single Phase (FPL Only), Three Phase or Network, 3 or 4 Wire

***K7 Three Phase K-Base applications are ONLY allowed at FPL
(GULF, DUKE, OGE and TECO do not allow any K-base installations)**

Participants:





Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase Service	Pos	Term	Bypass	Config
Durham	100 UTZ-6R1131C-FL	1 Ov/Un	6	4	N	1
Durham	100 UTZ-xR1121C-FL (x=2-5)	1 Ov/Un	2-5	4	N	1
Durham	125 UATZ-RS101C-FL	1 Ov/Un	1	4	N	1 Al
Durham	125 UTZ-RS101C-FL	1 Ov/Un	1	4	N	1
Durham	200 UAT-4300T-FL	3 Over	1	4	Y	1, Al
Durham	200 UAT-H4203x-FL (x=B or T)	1 Over	1	4	Y	1 Al
Durham	200 UAT-H4213x-FL (x=C or U)	1 Ov/Un	1	4	Y	1 Al
Durham	200 UAT-H5203x-FL	1 Over	1	5	Y	3,3a,b Al
Durham	200 UAT-H5213x-FL (x=C or U)	1 Ov/Un	1	5	Y	3,3a,b Al
Durham	200 UAT-H7203x-FL (x=B or T)	3 Over	1	7	Y	4 Al
Durham	200 UAT-H7213x-FL (x=C or U)	3 Ov/Un	1	7	Y	4 Al
Durham	200 UAT-RS202B-FL	1 Over	1	4	N	1 Al
Durham	200 UAT-RS212C-FL	1 Ov/Un	1	4	N	1 Al
Durham	200 UAT-RS213A-FL	1 Under	1	4	N	1 Al
Durham	200 UAT-RS213C-FL	1 Ov/Un	1	4	N	1 Al
Durham	200 UAT-RS223A-FL	1 Under	1	4	N	1 Al
Durham	200 UT-4R2352U-FL	1 Ov/Un	4	4	N	1
Durham	200 UT92197CC-FL	1 Ov/Un	1	4	N	1
Durham	200 UT-H4203x-FL (x=B or T)	1 Over	1	4	Y	1
Durham	200 UT-H4213x-FL (x=C or U)	1 Ov/Un	1	4	Y	1
Durham	200 UT-H5203x-FL (x=B or T)	1 Over	1	5	Y	3,3a,b Al
Durham	200 UT-H5213x-FL (x=C or U)	1 Ov/Un	1	5	Y	3,3a,b Al
Durham	200 UT-H7203x-FL (x=B or T)	3 Over	1	7	Y	4
Durham	200 UT-RS213A-FL	1 Under	1	4	Y	1
Durham	200 UT-RS223A-FL	1 Under	1	4	N	1
Durham	200 UT-xR2332U-FL (x=2-3)	1 Ov/Un	2-3	4	N	1
Durham	200 UT-xR2392UU-FL (x=5-6)	1 Ov/Un	5-6	4	N	1
Durham	320 UAT-H5330U-FL	1 Ov/Un	1	5	Y	3,3a,b Al
Durham	400 1008836	1 Ov/Un	1	4	Y	1
Durham	400 1008837	1 Ov/Un	1	4	Y	1 Al
Durham	400 UAT-H5300T-FL	1 Over	1	5	Y	3,3a,b,Al
Durham	400 UAT-H7300T-FL	3 Over	1	7	Y	4 Al
Durham	400 UAT-H7330U-FL	3 Ov/Un	1	7	Y	4 Al
Durham	400 UT-H4300T-FL	1 Over	1	4	Y	1



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Durham	400 UT-H5300T-FL	1	Over	1	5	Y	3,3a,b
Durham	400 UT-H5330U-FL	1	Ov/Un	1	5	Y	3,3a,b
Durham	400 UT-H7300T-FL	3	Over	1	7	Y	4
Durham	400 UT-H7330U-FL	3	Ov/Un	1	7	Y	4
Eaton B-Line	100 ECCB10L25A3xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	5	Y	3a
Eaton B-Line	100 ECCB10L27A3xx1F (xx=GR, AL, S4, S6)	3	OH/UG	1	7	Y	4
Eaton B-Line	100 ENCB10L25A3xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	5	N	1,2
Eaton B-Line	100 HEC10432Cxx1F (xx=GR, AL, S4, S6)	1	OH/UG	2	4	Y	3
Eaton B-Line	100 HEC10433Cxx1F (xx=GR, AL, S4, S6)	1	OH/UG	3	4	Y	3
Eaton B-Line	100 HEN10432Lxx1F (xx=GR, AL, S4, S6)	1	OH/UG	2	4	N	3
Eaton B-Line	100 HEN10433Lxx1F (xx=GR, AL, S4, S6)	1	OH/UG	3	4	N	3
Eaton B-Line	100 HEN10434Lxx1F (xx=GR, AL, S4, S6)	1	OH/UG	4	4	N	3
Eaton B-Line	100 HEN10435Lxx1F (xx=GR, AL, S4, S6)	1	OH/UG	5	4	N	3
Eaton B-Line	100 HEN10436Lxx1F (xx=GR, AL, S4, S6)	1	OH/UG	6	4	N	3
Eaton B-Line	125 EC12L53xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	5	Y	3,3a,b
Eaton B-Line	125 EN12L41xx1F (xx=GR, AL, S4, S6)	1	OH	1	4	N	1
Eaton B-Line	125 EN12L42xx1F (xx=GR, AL, S4, S6)	1	UG	1	4	N	1
Eaton B-Line	125 EN12L43xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	4	N	1
Eaton B-Line	125 EN12L51xx1F (xx=GR, AL, S4, S6)	1	OH	1	5	N	1,2
Eaton B-Line	125 EN12L52xx1F (xx=GR, AL, S4, S6)	1	UG	1	5	N	1,2
Eaton B-Line	125 EN12L53xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	5	N	1,2
Eaton B-Line	125 VENMP12432Lxx1F (xx=GR, AL, S4, S6)	1	OH/UG	2	4	N	3
Eaton B-Line	125 VENMP12433Lxx1F (xx=GR, AL, S4, S6)	1	OH/UG	3	4	N	3
Eaton B-Line	125 VENMP12434Cxx1F (xx=GR, AL, S4, S6)	1	OH/UG	4	4	N	3
Eaton B-Line	125 VENMP12435Cxx1F (xx=GR, AL, S4, S6)	1	OH/UG	5	4	N	3
Eaton B-Line	125 VENMP12436Cxx1F (xx=GR, AL, S4, S6)	1	OH/UG	6	4	N	3
Eaton B-Line	150 ENCB15L25A3xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	5	N	1,2
Eaton B-Line	200 EL20L53xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	5	Y	3,3a,b
Eaton B-Line	200 EL20L73xx1F (xx=GR, AL, S4, S6)	3	OH/UG	1	7	Y	4
Eaton B-Line	200 ELCB20L25A3xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	5	Y	3,3a
Eaton B-Line	200 ELCB20L27A3xx1F (xx=GR, AL, S4, S6)	3	OH/UG	1	7	Y	4
Eaton B-Line	200 EN20L41xx1F (xx=GR, AL, S4, S6)	1	OH	1	4	N	1
Eaton B-Line	200 EN20L42xx1F (xx=GR, AL, S4, S6)	1	UG	1	4	N	1
Eaton B-Line	200 EN20L43xx1F (xx=GR, AL, S4, S6)	1	OH/UG	1	4	N	1
Eaton B-Line	200 EN20L51xx1F (xx=GR, AL, S4, S6)	1	OH	1	5	N	1,2
Eaton B-Line	200 EN20L52xx1F (xx=GR, AL, S4, S6)	1	UG	1	5	N	1,2

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps	Catalog Number		Phase	Service	Pos	Term	Bypass	Config
Eaton B-Line	200	EN20L53xx1F	(xx=GR, AL, S4, S6)	1	OH/UG	1	5	N	1,2
Eaton B-Line	200	ENCB20L25A3xx1F	(xx=GR, AL, S4, S6)	1	OH/UG	1	5	N	1,2
Eaton B-Line	200	HEL20432Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	2	4	Y	3
Eaton B-Line	200	HEL20433Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	3	4	Y	3
Eaton B-Line	200	HEL20434Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	4	4	Y	3
Eaton B-Line	200	HEL20435Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	5	4	Y	3
Eaton B-Line	200	HEL20436Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	6	4	Y	3
Eaton B-Line	200	HEL20732Cxx1F	(xx=GR, AL, S4, S6)	3	OH/UG	2	7	Y	4
Eaton B-Line	200	HEL20733Cxx1F	(xx=GR, AL, S4, S6)	3	OH/UG	3	7	Y	4
Eaton B-Line	200	HEL20734Cxx1F	(xx=GR, AL, S4, S6)	3	OH/UG	4	7	Y	4
Eaton B-Line	200	HEL20735Cxx1F	(xx=GR, AL, S4, S6)	3	OH/UG	5	7	Y	4
Eaton B-Line	200	HEL20736Cxx1F	(xx=GR, AL, S4, S6)	3	OH/UG	6	7	Y	4
Eaton B-Line	200	VENMP20432Lxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	2	4	N	3
Eaton B-Line	200	VENMP20433Lxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	3	4	N	3
Eaton B-Line	200	VENMP20434Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	4	4	N	3
Eaton B-Line	200	VENMP20435Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	5	4	N	3
Eaton B-Line	200	VENMP20436Cxx1F	(xx=GR, AL, S4, S6)	1	OH/UG	6	4	N	3
Eaton B-Line	400	EL32T53xx1F	(xx=GR, AL, S4, S6)	1	OH/UG	1	5	Y	3,3a
Eaton B-Line	400	EL32T56xx1F	(xx=GR, AL, S4, S6)	1	OH/UG	1	5	Y	3,3a
Eaton B-Line	400	EL32T75xx1F	(xx=GR, AL, S4, S6)	3	OH/UG	1	7	Y	4
Eaton B-Line	400	EL32T76xx1F	(xx=GR, AL, S4, S6)	3	OH/UG	1	7	Y	4
Eaton B-Line	400	ELCB32C25A5xx1F	(xx=GR, AL, S4, S6)	1	OH/UG	1	5	Y	3,3a
Eaton-Cutler Hammer	100	MB1224B100BTS		1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	100	UATZxR1121CFLCH	(x = 2 - 5)	1	Ov/Un	2-5	4	N	1 AL
Eaton-Cutler Hammer	100	UATZ-xR1121CFLCH	(x=2-5)	1	Ov/Un	2-5	4	N	1 Al
Eaton-Cutler Hammer	125	1MMx12RP, RCP, RRLP or RRLCP	(x=3-6)	1	Ov/Un	3-6	4	N	1
Eaton-Cutler Hammer	125	1MPx124RP, RRLP or RRLCP	(x=3-4)	1	Ov/Un	3-4	4	N	1
Eaton-Cutler Hammer	125	1MPx126RP, RRLP or RRLCP	(x=5-6)	1	Ov/Un	5-6	4	N	1
Eaton-Cutler Hammer	125	3MMx12R12P	(x=2-6)	1	Ov/Un	2-6	4	N	1
Eaton-Cutler Hammer	125	3MMx12R12R12P	(x=2-6)	1	Ov/Un	2-6	4	N	1
Eaton-Cutler Hammer	125	3MMx12RCP	(x=2-6)	1	Ov/Un	2-6	4	N	1
Eaton-Cutler Hammer	125	3MMx12RP	(x=2-6)	1	Ov/Un	2-6	4	N	1
Eaton-Cutler Hammer	125	3MMx12RRRLCP	(x=2-6)	1	Ov/Un	2-6	4	N	1
Eaton-Cutler Hammer	125	3MMx12RRRLP	(x=2-6)	1	Ov/Un	2-6	4	N	1
Eaton-Cutler Hammer	125	CHR (POWER OUTLET PANEL)		1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	125	MBT48B125BTS		1	Ov/Un	1	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Eaton-Cutler Hammer	125 UATZ-RS101C-FLCH	1	Ov/Un	1	4	N	1 Al
Eaton-Cutler Hammer	125 UT-RS101xE (x=B,C)	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	125 UTZ-RS101C-FLCH	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	150 MB816B150BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	150 MBB150BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	150 MBT48B150BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 1MMx20RRLP or RRLCP (x=3-4)	1	Ov/Un	3-4	4	N	3
Eaton-Cutler Hammer	200 1MP2204RP, RRLP or RRLCP	1	Ov/Un	2	4	N	1
Eaton-Cutler Hammer	200 1MPx206RP, RRLP or RRLCP (x=3-6)	1	Ov/Un	3-6	4	N	1
Eaton-Cutler Hammer	200 3MMx20R12P (x=2-5)	1	Ov/Un	2-5	4	N	3
Eaton-Cutler Hammer	200 3MMx20R12RLP (x=2-5)	1	Ov/Un	2-5	4	N	3
Eaton-Cutler Hammer	200 3MMx20RCP (x=2-5)	1	Ov/Un	2-5	4	N	3
Eaton-Cutler Hammer	200 3MMx20RP (x=2-5)	1	Ov/Un	2-5	4	N	3
Eaton-Cutler Hammer	200 3MMx20RRLCP (x=2-5)	1	Ov/Un	2-5	4	N	3
Eaton-Cutler Hammer	200 3MMx20RRLP (x=2-5)	1	Ov/Un	2-5	4	N	3
Eaton-Cutler Hammer	200 CMB1212B200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 CMB1212L200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 CMB1212P200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 CMB2424B200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 CMB2436B200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MB1212L200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MB1212L200BTSA	1	Ov/Ln	1	4	N	1 Al
Eaton-Cutler Hammer	200 MB2040B200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MB2040P200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MB4040B200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MB816B200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MB816P200BTS or BTSCU	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MBB200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MBP200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 MBT48B200BTS	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 UAT-4R2352UFLCH	1	Ov/Un	4	4	N	1 AL
Eaton-Cutler Hammer	200 UAT-H4203x-FLCH (x=B or T)	1	Over	1	4	Y	1 Al
Eaton-Cutler Hammer	200 UAT-H5203x-FLCH (x=B or T)	1	Over	1	5	Y	3,3a,b Al
Eaton-Cutler Hammer	200 UAT-H7203x-FLCH (x=B or T)	3	Over	1	7	Y	4 Al
Eaton-Cutler Hammer	200 UAT-RS202B-FLCH	1	Over	1	4	N	1 Al
Eaton-Cutler Hammer	200 UAT-RS212C-FLCH	1	Ov/Un	1	4	N	1 Al

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Eaton-Cutler Hammer	200 UAT-RS213A-FLCH	1	Under	1	4	N	1 Al
Eaton-Cutler Hammer	200 UAT-RS213C-FLCH	1	Ov/Un	1	4	N	1 Al
Eaton-Cutler Hammer	200 UAT-RS223A-FLCH	1	Under	1	4	N	1 Al
Eaton-Cutler Hammer	200 UAT-xR2332U-FLCH (x=2-3)	1	Ov/Un	2-3	4	N	1
Eaton-Cutler Hammer	200 UATxR2392UUFLCH (x=5-6)	1	Ov/Un	5-6	4	N	1 Al
Eaton-Cutler Hammer	200 UAT-y4213x-FLCH (y=E or H, where x=C or U)	1	Ov/Un	1	4	Y	1 Al
Eaton-Cutler Hammer	200 UAT-y5213x-FLCH (y=E or H, where x=C or U)	1	Ov/Un	1	5	Y	3,3a,b Al
Eaton-Cutler Hammer	200 UAT-y7213x-FLCH (y=E or H, where x=C or U)	3	Ov/Un	1	7	Y	4 Al
Eaton-Cutler Hammer	200 UT-4R2352U-FLCH	1	Ov/Un	4	4	N	1
Eaton-Cutler Hammer	200 UT92197CC-FL-CH	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 UT-RS202B-FLCH	1	Over	1	4	N	1
Eaton-Cutler Hammer	200 UT-RS212C-FLCH	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 UT-RS213A-FLCH	1	Under	1	4	N	1
Eaton-Cutler Hammer	200 UT-RS213CE	1	Ov/Un	1	4	N	1
Eaton-Cutler Hammer	200 UT-RS213C-FLCH	1	Ov/Un	1	4/5	N	1, 2
Eaton-Cutler Hammer	200 UT-RS223A-FLCH	1	Under	1	4	N	1
Eaton-Cutler Hammer	200 UT-xR2332U-FLCH (x=2-3)	1	Ov/Un	2-3	4	N	1
Eaton-Cutler Hammer	200 UT-xR2392UU-FLCH (x=5-6)	1	Ov/Un	5-6	4	N	1
Eaton-Cutler Hammer	200 UT-y4203x-FLCH (y=E or H, where x=B or T)	1	Over	1	4	Y	1
Eaton-Cutler Hammer	200 UT-y4213x-FLCH (y=E or H, where x=C or U)	1	Ov/Un	1	4	Y	1
Eaton-Cutler Hammer	200 UT-y5203x-FLCH (y=E or H, where x=B or T)	1	Over	1	5	Y	3,3a,b
Eaton-Cutler Hammer	200 UT-y5213x-FLCH (y=E or H, where x=C or U)	1	Ov/Un	1	5	Y	3,3a,b
Eaton-Cutler Hammer	200 UT-y7203x-FLCH (y=E or H, where x=B or T)	3	Over	1	7	Y	4
Eaton-Cutler Hammer	200 UT-y7213x-FLCH (where y=E or H, x=C or U)	3	Ov/Un	1	7	Y	4
Eaton-Cutler Hammer	225 35MMx20R12 or R12C (x=1-4)	1	Ov/Un	1-4	5	Y	3,3a
Eaton-Cutler Hammer	225 37MMx20R12 or R12C (x=1-4)	3	Ov/Un	1-4	7	Y	4
Eaton-Cutler Hammer	400 1008836CH	1	Ov/Un	1	4	Y	1
Eaton-Cutler Hammer	400 1008837CH	1	Ov/Un	1	4	Y	1 Al
Eaton-Cutler Hammer	400 1011619CH	1	Ov/Un	1	4	Y	1
Eaton-Cutler Hammer	400 35MM140R1240	1	Under	1	5	Y	3
Eaton-Cutler Hammer	400 35MM240R1240	1	Under	2	5	Y	3
Eaton-Cutler Hammer	400 37MM140R1240	3	Under	1	7	Y	4
Eaton-Cutler Hammer	400 37MM240R1240	3	Under	1	7	Y	4
Eaton-Cutler Hammer	400 CG1212P400BSL	1	Under	1	4	Y	3
Eaton-Cutler Hammer	400 CG404242SHL	1	Under	1	4	Y	3
Eaton-Cutler Hammer	400 CG40SHL	1	Under	1	4	Y	3

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Eaton-Cutler Hammer	400 HP404040SHL	1	Under	1	4	Y	3
Eaton-Cutler Hammer	400 HP40SHL	1	Under	1	4	Y	3
Eaton-Cutler Hammer	400 HP816Px00BSL (x = 3 or 4)	1	Under	1	4	Y	3
Eaton-Cutler Hammer	400 HPCx046SHLG (x= 3 or 4)	1	Ov/Un	1	4	y	3
Eaton-Cutler Hammer	400 HPCx0SHL (x= 3 or 4)	1	Ov/Un	1	4	y	3
Eaton-Cutler Hammer	400 UAT-H4300T-FLCH	1	Over	1	4	Y	1 Al
Eaton-Cutler Hammer	400 UAT-H5300T-FLCH	1	Over	1	5	Y	3,3a,b Al
Eaton-Cutler Hammer	400 UAT-H5330U-FLCH	1	Ov/Un	1	5	Y	3,3a,b Al
Eaton-Cutler Hammer	400 UAT-H7300T-FLCH	3	Over	1	7	Y	4 Al
Eaton-Cutler Hammer	400 UAT-H7330U-FLCH	3	Ov/Un	1	7	Y	4 Al
Eaton-Cutler Hammer	400 UT-H4300T-FLCH	1	Over	1	4	Y	1
Eaton-Cutler Hammer	400 UTH43068TFLCH	1	Ov/Un	1	4	Y	1
Eaton-Cutler Hammer	400 UT-H5300T-FLCH	1	Over	1	5	Y	3,3a,b
Eaton-Cutler Hammer	400 UT-H5330U-FLCH	1	Ov/Un	1	5	Y	3,3a,b
Eaton-Cutler Hammer	400 UT-H7300T-FLCH	3	Over	1	7	Y	4
Eaton-Cutler Hammer	400 UT-H7330U-FLCH	3	Ov/Un	1	7	Y	4
Eaton-Cutler Hammer	400 UTH73368UFLCH	3	Ov/Un	1	7	Y	4
Eaton-Cutler Hammer	600 CH9526K7 (Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5
Eaton-Cutler Hammer	600 CH9527K7 (Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5 Al
Elec.Prod.	100 RVP-xxxx-FPL	1	Under	1	4	N	1
Elec.Prod.	200 MHP-xxxx-FPL	1	Under	1	4	N	1
Emerson	125 MESBGFXLW11FBZ1	1	Under	1	5	Y	3a
Emerson	125 MESBGFXLW11FBZ1P	1	Under	1	5	Y	3a
Emerson	125 MESBGFXLW11KBZ1	1	Under	1	5	Y	3a
Emerson	125 MESBGFXLW11KBZ1P	1	Under	1	5	Y	3a
Emerson	200 MESBAATLW11FBZ1	1	Under	1	5	Y	3a
Emerson	200 MESBAATLW11FBZ1P	1	Under	1	5	Y	3a
Emerson	200 MESBAATLW11KBZ1	1	Under	1	5	Y	3a
Emerson	200 MESBAATLW11KBZ1P	1	Under	1	5	Y	3a
General Electric	(2) 150TSDR830USCU	1	Under	1	4/5	Y	1,2
General Electric	100 TM10RMCFMG	1	Ov/Un	1	4	N	1
General Electric	100 UTZ-6R1131CFLGE	1	Ov/Un	6	4	N	1
General Electric	100 UTZ-xR1121CFLGE (x=2-5)	1	Ov/Un	6	4/5	N	1,2
General Electric	125 TM12RMCFMG	1	Ov/Un	1	4	N	1
General Electric	125 TMM2212RF	1	Ov/Un	2	4	N	1
General Electric	125 TMM4x12RF (x=3-4)	1	Under	3-4	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
General Electric	125 TMM6x12RF (x=5-6)	1	Under	5-6	4	N	1
General Electric	125 TMMR2212RF	1	Ov/Un	2	4/5	N	1,2
General Electric	125 TMMR4x12RF (x=3-4)	1	Under	3-4	4/5	N	1,2
General Electric	125 TMMR6x12RF (x=5-6)	1	Under	5-6	4/5	N	1,2
General Electric	125 TMPR12520RBUS	1	Ov/Un	5	5	N	2
General Electric	125 TMPR12x12RF (x=2-6)	1	Ov/Un	2-6	5	N	2
General Electric	125 TMPR8520RBUS	1	Ov/Un	5	5	N	2
General Electric	125 TMPR8x12RF (x=2-6)	1	Ov/Un	2-6	4	N	1,2
General Electric	125 UATZ-RS101CFLGE	1	Ov/Un	1	4	N	1 Al
General Electric	125 UTZ-RS101C-FLGE	1	Ov/Un	1	4	N	1
General Electric	150 TM15RMC FMG	1	Ov/Un	1	4	N	1
General Electric	150 TSMR415CSFLFMG	1	Ov/Un	1	5	N	2
General Electric	150 TSMR815CSFLFMG	1	Ov/Un	1	5	N	2
General Electric	200 TM20RMC FMG	1	Ov/Un	1	4	N	1
General Electric	200 TMM6x20RF (x=3-4)	1	Under	3-4	4	N	1
General Electric	200 TMMR4220RF	1	Under	2	5	N	2
General Electric	200 TMMR6x20RF (x=3-6)	1	Under	3-6	5	N	2
General Electric	200 TMPR12x20RF (x=4-5)	1	Ov/Un	4-5	5	N	2
General Electric	200 TMPR8x20RF (x=2-5)	1	Ov/Un	2-5	5	N	2
General Electric	200 TSLR1220FSAL	1	Ov/Un	1	4/5	N	1, 2
General Electric	200 TSMR2020CSCUFMG	1	Ov/Un	1	4/5	N	1,2
General Electric	200 TSMRx20CSFLFMG (x = 4, 8)	1	Ov/Un	1	4/5	N	1,2
General Electric	200 UAT-H4203x-FLGE (x=B or T)	1	Over	1	4	Y	1 Al
General Electric	200 UAT-H4213x-FLGE (x=C or U)	1	Ov/Un	1	4	Y	1 Al
General Electric	200 UAT-H5203x-FLGE (x=B or T)	1	Over	1	5	Y	3,3a,b Al
General Electric	200 UAT-H5213x-FLGE (x=C or U)	1	Ov/Un	1	5	Y	3,3a,b Al
General Electric	200 UAT-H7203x-FLGE (x=B or T)	3	Over	5-6	7	Y	4 Al
General Electric	200 UAT-H7213x-FLGE (x=C or U)	1	Ov/Un	1	7	Y	4 Al
General Electric	200 UAT-RS202B-FLGE	1	Over	1	4	N	1 Al
General Electric	200 UAT-RS212C-FLGE	1	Ov/Un	1	4	N	1 Al
General Electric	200 UAT-RS213A-FLGE	1	Under	1	4	N	1 Al
General Electric	200 UAT-RS213C-FLGE	1	Ov/Un	1	4	N	1 Al
General Electric	200 UAT-RS223A-FLGE	1	Under	1	4	N	1 Al
General Electric	200 UT-4R2352U-FLGE	1	Ov/Un	4	4	N	1
General Electric	200 UT92197CC-FL-GE	1	Ov/Un	1	4	N	1
General Electric	200 UT-H4203x-FL-GE (x=B or T)	1	Over	1	4	Y	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
General Electric	200 UT-H4213x-FL-GE (x=C or U)	1	Ov/Un	1	4	Y	1
General Electric	200 UT-H5203x-FL-GE (x=B or T)	1	Over	1	5	Y	3,3a,b
General Electric	200 UT-H5213x-FL-GE (x=C or U)	1	Ov/Un	1	5	Y	3,3a,b
General Electric	200 UT-H7203x-FL-GE (x=B or T)	1	Over	1	7	Y	4
General Electric	200 UT-RS213A-FL-GE	1	Under	1	4	N	1
General Electric	200 UT-RS213C-FL-GE	1	Ov/Un	1	4	N	1
General Electric	200 UT-RS223A-FL-GE	1	Under	1	4	N	1
General Electric	200 UT-xR2332U-FLGE (x=2-3)	1	Ov/Un	1	4	N	1
General Electric	200 UT-xR2392UUFLGE (x=5-6)	1	Ov/Un	1	4	N	1
General Electric	225 TMPR12x22R (x=1-4)	1	Ov/Un	1-4	5	Y	3,3a
General Electric	225 TMPR312x22RF (x=1-4)	3	Ov/Un	1-4	7	Y	4
General Electric	400 1008836-GE	1	Ov/Un	1	4	Y	1
General Electric	400 1008837-GE	1	Ov/Un	1	4	Y	1 Al
General Electric	400 TMPR12x40RB (x=1-2)	1	Ov/Un	1-2	5	N	3,3a
General Electric	400 TMPR312x40RB (x=1-2)	3	Ov/Un	1-2	7	Y	4
General Electric	400 TSDR840UFCU	1	Under	1	4/5	Y	1,2
General Electric	400 UAT-H4300T-FLGE	1	Over	1	4	Y	1 Al
General Electric	400 UAT-H5300T-FLGE	1	Over	1	5	Y	3,3a,b Al
General Electric	400 UAT-H5330U-FLGE	1	Ov/Un	1	5	Y	3,3a Al
General Electric	400 UAT-H7300T-FLGE	3	Over	1	7	Y	4 Al
General Electric	400 UAT-H7330U-FLGE	3	Ov/Un	1	7	Y	4 Al
General Electric	400 UT-H4300T-FL-GE	1	Over	1	4	Y	1
General Electric	400 UT-H5300T-FL-GE	1	Over	1	5	Y	3,3a,b
General Electric	400 UT-H5330U-FL-GE	1	Ov/Un	1	5	Y	3,3a,b
General Electric	400 UT-H7300T-FL-GE	3	Over	1	7	Y	4
General Electric	400 UT-H7330U-FL-GE	3	Ov/Un	1	7	Y	4
Leviton**	150 LP815-5MC	1	0v/Un	1	5	Y	2
Leviton**	150 LP815-LMC	1	0v/Un	1	4	Y	1
Leviton**	150 LP815-MC	1	Ov/Un	1	4	N	1
Leviton**	200 LP820-5MC	1	0v/Un	1	5	Y	2
Leviton**	200 LP820-LMC	1	0v/Un	1	4	Y	1
Leviton**	200 LP820-MC	1	0v/Un	1	4	N	1
Midwest	100 R075CB6010FMG	1	Un-Ped	1	4	N	1
Midwest	100 R075CP6010FMG	1	Un-Ped	1	4	N	1
Midwest	100 R102EN	1	Over	1	4	N	1
Midwest	100 RH75CB3FMG	1	Un-Ped	1	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Midwest	100 RH75CP3FMG	1	Un-Ped	1	4	N	1
Midwest	100 UTZ6R1131CFLMEP	1	Ov/Un	6	4	N	1
Midwest	100 UTZxR1121CFLMEP (x=2-5)	1	Ov/Un	2-5	4	N	1
Midwest	125 UATZRS101CFLMEP	1	Ov/Un	1	4	N	1 Al
Midwest	125 UTZ-RS101CFLMEP	1	Ov/Un	1	4	N	1
Midwest	150 R158CR2TLFMG	1	Ov/Un	1	4	N	1
Midwest	150 RS43308C (2x 150MB)	1	Ov/Un	1	4	Y	3
Midwest	200 R208CR2TLFMG	1	Ov/Un	1	4	N	1
Midwest	200 R256EB118FMG	1	Ov/Un	1	4	N	1, Al
Midwest	200 R256EB1FMG	1	Ov/Un	1	4	N	1
Midwest	200 R256EB1NFMG	1	Ov/Un	1	4	N	1
Midwest	200 RS45500C (2 X 200MB)	1	Under	1	4	Y	3
Midwest	200 RS45508C (2 X 200MB)	1	Under	1	4	Y	3
Midwest	200 UAT-H4203xFLMEP (x=B or T)	1	Over	1	4	Y	1 Al
Midwest	200 UAT-H4213xFLMEP (x=C or U)	1	Ov/Un	1	4	Y	1 Al
Midwest	200 UAT-H5203xFLMEP (x=B or T)	1	Over	1	5	Y	3,3a,b Al
Midwest	200 UAT-H5213xFLMEP (x=C or U)	1	Ov/Un	1	5	Y	3,3a,b Al
Midwest	200 UAT-H7203x-FLMEP (x=B or T)	3	Over	1	7	Y	4 Al
Midwest	200 UAT-H7213xFLMEP (x=C or U)	3	Ov/Un	1	7	Y	4 Al
Midwest	200 UAT-RS202BFLMEP	1	Over	1	4	N	1 Al
Midwest	200 UAT-RS212CFLMEP	1	Ov/Un	1	4	N	1 Al
Midwest	200 UAT-RS213AFLMEP	1	Under	1	4	N	1 Al
Midwest	200 UAT-RS213CFLMEP	1	Ov/Un	1	4	N	1 Al
Midwest	200 UAT-RS223AFLMEP	1	Under	1	4	N	1 Al
Midwest	200 UT-4R2352UFLMEP	1	Ov/Un	4	4	N	1
Midwest	200 UT92197CC-FLMEP	1	Ov/Un	1	4	N	1
Midwest	200 UT-H4203x-FLMEP (x=B or T)	1	Over	1	4	Y	1
Midwest	200 UT-H4213x-FLMEP (x=C or U)	1	Ov/Un	1	4	Y	1
Midwest	200 UT-H5203x-FLMEP (x=B or T)	1	Over	1	5	Y	3,3a,b
Midwest	200 UT-H5213x-FLMEP (x=C or U)	1	Ov/Un	1	5	Y	3,3a,b
Midwest	200 UT-H7203x-FLMEP (x=B or T)	3	Over	1	7	Y	4
Midwest	200 UT-RS213A-FLMEP	1	Under	1	4	N	1
Midwest	200 UT-RS213C-FLMEP	1	Ov/Un	1	4	N	1
Midwest	200 UT-RS223A-FLMEP	1	Under	1	4	N	
Midwest	200 UT-xR2332UFLMEP (x=2-3)	1	Ov/Un	2-3	4	N	1
Midwest	200 UTxR2392UFLMEP (x = 5-6)	1	Ov/Un	5-6	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Midwest	400 1008836-MEP	1	Ov/Un	1	4	Y	1
Midwest	400 1008837-MEP	1	Ov/Un	1	4	Y	1 Al
Midwest	400 RS45524CFMG	1	Under	1	4/5	Y	1,2
Midwest	400 UAT-H4300TFLMEP	1	Over	1	4	Y	1 Al
Midwest	400 UAT-H5300TFLMEP	1	Over	1	5	Y	3,3a,b Al
Midwest	400 UAT-H5330UFLMEP	1	Ov/Un	1	5	Y	3,3a,b Al
Midwest	400 UAT-H7300TFLMEP	3	Over	1	7	Y	4 Al
Midwest	400 UAT-H7330UFLMEP	3	Ov/Un	1	7	Y	4 Al
Midwest	400 UT-H4300T-FLMEP	1	Over	1	4	Y	1
Midwest	400 UT-H5300T-FLMEP	1	Over	1	5	Y	3,3a,b
Midwest	400 UT-H5330UFLMEP	1	Ov/Un	1	5	Y	3,3a,b
Midwest	400 UT-H7300TFLMEP	3	Over	1	7	Y	4
Midwest	400 UT-H7330UFLMEP	3	Ov/Un	1	7	Y	4
Milbank	100 U349y-XL-HSP (y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	100 U513y-O-100P-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	100 U513y-O-100S-10GR-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	100 U513y-O-100S-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	100 U5842-RL-100-HSP	1	Over	1	4	N	1
Milbank	100 U6266-XTL-100-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	100 UAP349y-XL-HSP (y=2-6)	1	Ov/Un	2-6	4/5	N	1,2 Al
Milbank	125 U285y-X-HSP (y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	125 U3505-XL-HSP	1	Ov/Un	1	5	Y	3,3a
Milbank	125 U3505-XL-TG-HSP	1	Ov/Un	1	5	Y	3,3a
Milbank	125 U3506-XL-TG-HSP	3	Ov/Un	1	7	Y	4
Milbank	125 U513y-O-125P-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	125 U513y-O-125S-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	125 U8435-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	125 UAP3505-XL-TG-HSP	1	Ov/Un	1	5	Y	3,3a Al
Milbank	125 UAP3506-XL-TG-HSP	3	Ov/Un	1	7	Y	4 Al
Milbank	125 UAP8435-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2 Al
Milbank	150 U123y-X-HSP (y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	150 U3312-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	150 U513y-O-150P-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	150 U513y-O-150S-10GR-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	150 U513y-O-150S-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	150 U5842-RL-150-HSP	1	Over	1	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Milbank	150 U6266-XTL-150-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	150 UAP123y-X-HSP (y=2-3)	1	Ov/Un	2-3	4/5	N	1,2 Al
Milbank	200 CP3B5####x##### (x= D,P,R,S)(#=Cust. Option)	3	Un-Ped	1	7	Y	4 SS
Milbank	200 U125Y-X-HSP (y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	200 U1980-O-HSP	1	Under	1	4/5	N	1,2
Milbank	200 U273y-XT-HSP (y=2-6)	3	Ov/Un	2-6	7	Y	4
Milbank	200 U286y-X-HSP (y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	200 U287y-XT-HSP (y=2-6)	1	Ov/Un	2-6	5	Y	3,3a
Milbank	200 U3296-X-HSP	1	Ov/Un	1	5	Y	3,3a,3b
Milbank	200 U3306-X-HSP	3	Ov/Un	1	7	Y	4
Milbank	200 U3850-XL-TG-HSP-PL	1	Ov/Un	1	4/5	N	1,2
Milbank	200 U5136-O-yyy-FMG (yyy=41,55,75,332,552)	1	Un-Ped	1	4/5	N	1,2
Milbank	200 U5137-O-yyy-FMG (yyy=41,55,75,332,552)	1	Un-Ped	2	4/5	N	1,2
Milbank	200 U513y-O-200P-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	200 U513y-O-200S-10GR-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	200 U513y-O-200S-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	200 U513y-O-FMG (y=6-9)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	200 U5842-RL-200-HSP	1	Over	1	4	N	1
Milbank	200 U6266-XTL-200-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	200 U7021-RL-TG-HSP	1	Over	1	4/5	N	1,2
Milbank	200 U7040-O-TG-HSP	1	Under	1	4	N	1,2
Milbank	200 U7040-XL-TG-5T-HSP	1	Ov/Un	1	5	N	1,2
Milbank	200 U7040-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	200 U7043-XL-TG	1	Ov/Un	1	4/5	N	1,2
Milbank	200 U9550-RRL-QG-HSP	1	Over	1	5	Y	3,3a,b
Milbank	200 U9551-X-QG-HSP	1	Ov/Un	1	5	Y	3,3a,b
Milbank	200 U9700-RRL-QG-HSP	3	Over	1	7	Y	4
Milbank	200 U9701-X-QG-HSP	3	Ov/Un	1	7	Y	4
Milbank	200 U9801-X-QG -HSP	1	Ov/Un	1	4	Y	1,2
Milbank	200 UAP125y-X-HSP (y=2-6)	1	Ov/Un	2-6	4/5	Y	1,2 Al
Milbank	200 UAP1980-O-HSP	1	Under	1	4/5	N	1,2 Al
Milbank	200 UAP3296-X-HSP	1	Ov/Un	1	5	Y	3,3a,b Al
Milbank	200 UAP3306-X-HSP	3	Ov/Un	1	7	Y	4 Al
Milbank	200 UAP5024-XL	1	Ov/Un	1	4	N	1 Al
Milbank	200 UAP5024-XL-FMG	1	Ov/Un	1	4	N	1 Al
Milbank	200 UAP7021-RL-TG-HSP	1	Over	1	4/5	N	1,2 Al

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Milbank	200 UAP7040-O-TG-HSP	1	Under	1	4/5	N	1,2 Al
Milbank	200 UAP7040-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2 Al
Milbank	200 UAP9550-RRL-QG-HSP	1	Over	1	5	Y	3,3a,b Al
Milbank	200 UAP9551-X-QG-HSP	1	Ov/Un	1	5	Y	3,3a,b Al
Milbank	200 UAP9700-RRL-QG-HSP	3	Over	1	7	Y	4 Al
Milbank	200 UAP9701-X-QG-HSP	3	Ov/Un	1	7	Y	4 Al
Milbank	400 U1129-O-K3L-K2L-HSP	1	Under	1	4/5	Y	3,3a
Milbank	400 U2120-O-HSP	3	Ov/Un	1	7	Y	4
Milbank	400 U2120-X-HSP	3	Ov/Un	1	7	Y	4
Milbank	400 U2124-O-HSP	1	Under	1	4	Y	3
Milbank	400 U3313-X-HSP	1	Ov/Un	1	5	Y	3,3a
Milbank	400 U3566-X-HSP	3	Ov/Un	1	7	Y	4
Milbank	400 U3949-X-HSP	1	Over	1	5	Y	3,3a
Milbank	400 U4363-X-HSP	1	Over	1	4	Y	3
Milbank	400 U5864-X-HSP	1	Ov/Un	1	5	Y	3, 3a
Milbank	400 U5890-X-2/150-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U5890-X-2/200-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U5890-X-200-150-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U5891-X-2/150-MLK-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U5891-X-2/200-MLK-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U6115-X-2/200-K7L-HSP	3	Ov/Un	1	7	Y	4
Milbank	400 U6227-X-400-K3L-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U6229-X-400-K7L-HSP	3	Ov/Un	1	7	Y	3a
Milbank	400 U6267-X-2/100-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U6267-X-2/150-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U6267-X-2/200-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U6267-X-200 -150-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 U6272-X-HSP	1	Ov/Un	1	4	Y	3
Milbank	400 UAP2124-O-HSP	1	Under	1	4	Y	4 Al
Milbank	400 UAP3313-X-HSP	1	Ov/Un	1	5	Y	3,3a Al
Milbank	400 UAP3566-X-HSP	3	Ov/Un	1	7	Y	4 Al
Milbank	400 UAP3949-X-HSP	1	Over	1	5	Y	3,3a Al
Milbank	400 UAP5864-X-HSP	1	Ov/Un	1	5	Y	3, 3a Al
Milbank	400 UAP6272-X-HSP	1	Ov/Un	1	4	Y	3 Al
Milbank	600 U4667-X-8528 (Req. Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5
Milbank	600 U4667-X-9526 (Req. Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Milbank	600 UA4667-X-8529 (Req. Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5 Al
Milbank	600 UA4667-XT-9527 (Req. Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5 Al
Murray	100 RJ103AXF	1	Over	1	4	N	1
Murray	150 JA0408B1150RT	1	Ov/Un	1	4	N	1
Murray	150 JA0816B1150RCT	1	Ov/Un	1	4	N	1
Murray	150 JA0816B1150RTH	1	Ov/Un	1	4/5	N	1,2
Murray	200 JA0408B1200RT	1	Ov/Un	1	4	N	1
Murray	200 JA0606L1200R or RA	1	Ov/Un	1	4/5	N	1, 1 Al
Murray	200 JA0816B1200RCT	1	Ov/Un	1	4	N	1
Murray	200 JA0816B1200RTH	1	Ov/Un	1	4/5	N	1,2
Murray	200 JC0406L1200RH	1	Ov/Un	1	4/5	N	1, 2
Murray	200 RB103AR	1	Ov/Un	1	4/5	N	1,2
Murray	200 RH173CRF	1	Ov/Un	1	5	Y	3,3a
Murray	200 RH173GRF	3	Ov/Un	1	7	Y	4
Murray	200 RS103AVF	1	Under	1	4/5	N	1,2
Murray	200 RS103AXF	1	Over	1	4	N	1
Murray	400 JA0816B1350RLTM	1	Ov/Un	1	4/5	Y	1,2
Murray	400 JA0816B1400RLTM	1	Ov/Un	1	4/5	Y	1,2
Murray	400 JC0404L1400RLM	1	Ov/Un	1	4/5	Y	1,2
Siemens	125 SPxx11RJ (xx=22, 33, 44, 45, 46, 65, 66)	1	Ov/Un	2-6	4/5	N	1,2
Siemens	125 SUAT111-OGF	1	Over	1	4	N	1
Siemens	125 WMM44xxURNJ (xx=AB,BC, or CA)	3	Under	4	4/5	N	1,2
Siemens	125 WMM54xxURNJ (xx=AB,BC, or CA)	3	Under	5	4/5	N	1,2
Siemens	125 WMMx1125R (x=2-6)	1	Under	2-6	4/5	N	1,2
Siemens	125 WMMx2125RJ (x=2-6)	3	Under	2-6	5	N	2
Siemens	125 WP2211RJ	1	Mtr Ctr	2	5	N	2
Siemens	125 WP3311RJ	1	Mtr Ctr	3	5	N	2
Siemens	125 WP4X11RJ (x=4-6)	1	Mtr Ctr	4-6	5	N	2
Siemens	125 WP5411RJ	1	Mtr Ctr	4	5	N	2
Siemens	125 WP6x11RJ (x=5-6)	1	Mtr Ctr	5-6	5	N	2
Siemens	150 MC0202B1150R	1	Ov/Un	1	4/5	N	1,2
Siemens	150 MC0408B1150RT	1	Ov/Un	1	4	N	1
Siemens	150 MC0816B1150RCT	1	Ov/Un	1	4	N	1
Siemens	150 MC0816B1150RTH	1	Ov/Un	1	4/5	N	1,2
Siemens	150 MC2040B1150R	1	Ov/Un	1	4/5	N	1,2
Siemens	150 MC2040B1150RC	1	Ov/Un	1	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Siemens	150 MC2040B1500R	1	Ov/Un	1	4/5	N	1,2
Siemens	150 MM202B1150R	1	Ov/Un	1	4/5	N	1,2
Siemens	200 MC0202B1200R	1	Ov/Un	1	4/5	N	1,2
Siemens	200 MC0408B1200RT	1	Ov/Un	1	4	N	1
Siemens	200 MC0606L1200R or RA	1	Ov/Un	1	4/5	N	1, 1 AI
Siemens	200 MC0816B1200RCT	1	Ov/Un	1	4	N	1
Siemens	200 MC0816B1200RTH	1	Ov/Un	1	4/5	N	1,2
Siemens	200 MC2040B1200R	1	Ov/Un	1	4/5	N	1,2
Siemens	200 MC2040B1200RC	1	Ov/Un	1	4	N	1
Siemens	200 MC2040S1200JLC	1	Ov/Un	1	4/5	Y	3
Siemens	200 MM202B1200R	1	Ov/Un	1	4/5	N	1,2
Siemens	200 S40405-015F	1	Ov/Un	1	5	Y	3,3a
Siemens	200 S40407-015F	3	Ov/Un	1	7	Y	4
Siemens	200 SPxx12RJ (xx=42, 43, 44, 65, 66)	1	Ov/Un	2-6	4/5	N	1,2
Siemens	200 SUAT317-OGF	1	Over	1	4	N	1
Siemens	200 SUAT417-PGF	1	Under	1	4/5	N	1,2
Siemens	200 SUAT417-XGF	1	Ov/Un	1	4/5	N	1,2
Siemens	200 UAT417-XMF	1	Ov/Un	1	5	N	2
Siemens	200 UAT417-XMF	1	Ov/Un	1	5	N	2
Siemens	200 WMMx1225R (x=2-6)	1	Under	2-6	4/5	N	1,2
Siemens	200 WMMx2225RJ (x=2-6)	3	Under	2-6	5	N	2
Siemens	200 WP10612RJ	1	Mtr Ctr	6	4/5	N	1,2
Siemens	200 WP4x12RJ (x=2-4)	1	Mtr Ctr	2-4	4/5	N	1,2
Siemens	200 WP6x12RJ (x=4-6)	1	Mtr Ctr	4-6	4/5	N	1,2
Siemens	200 WP8612RJ	1	Mtr Ctr	6	4/5	N	1,2
Siemens	200 WPL10612RJ	1	Mtr Ctr	6	4/5	Y	3,3a
Siemens	200 WPL4x12RJ (x=2-4)	1	Mtr Ctr	2-4	4/5	Y	3,3a
Siemens	200 WPL6x12RJ (x=4-6)	1	Mtr Ctr	4-6	4/5	Y	3,3a
Siemens	200 WPL8612RJ	1	Mtr Ctr	6	4/5	Y	3,3a
Siemens	225 WML1x225RJ (x=1-4)	1	Ov/Un	1-4	4/5	Y	3,3a
Siemens	225 WMLx1225RJ (x=2-6)	1	Ov/Un	2-6	4/5	Y	3,3a
Siemens	225 WMLx2225RJ (x=1-4)	3	Under	1-4	7	Y	4
Siemens	225 WMLx2yz225RJ (x=2 or 4) (yz=AB, BC or CA)	3	Ov/Un	2 or 4	5	Y	3,3A
Siemens	225 WMLx3225RJ (x=1-4)	3	Under	1-4	7	Y	4
Siemens	250 WC2040B1TxR (x=1-9)	1	Under	1	4	N	1
Siemens	250 WC2040B1TxRJ (x=1-9)	1	Under	1	5	N	2

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Siemens	250 WC2040B2TxRJ (x=1-9)	1	Under	1	5	N	2
Siemens	250 WCL2040B1TxRJ (x=1-9)	1	Under	1	4/5	N	1,2
Siemens	250 WCL2040B2TxRJ (x=1-9)	1	Under	1	4/5	Y	3,3a
Siemens	250 WCL2442B3TxRJ (x=1-9)	3	Under	1	7	Y	4
Siemens	400 MC0408B1400RLTM	1	Ov/Un	1	4/5	Y	3,3a
Siemens	400 MC0816B1350RLTM	1	Ov/Un	1	4/5	Y	3,3a
Siemens	400 MC0816B1400RLTM	1	Ov/Un	1	4/5	Y	3,3a
Siemens	400 MC3042B1400SDL	1	Ov/Un	1	4	N	1
Siemens	400 MM0404L1400RLM	1	Ov/Un	1	4/5	Y	3,3a
Siemens	400 WML11400RJH	1	Ov/Un	1	5	Y	3a
Siemens	400 WML12400RJH	3	Ov/Un	1	5	Y	3a
Siemens	400 WML13400RJ	3	Ov/Un	1	7	Y	4
Siemens	400 WML13400RJFS	3	Ov/Un	1	7	Y	4
Siemens	400 WML13400RJH	3	Ov/Un	1	7	Y	4
Siemens	400 WMLxy400RJ where (x=1-2) (y=1-2)	1	Ov/Un	1	4/5	Y	3,3a
Siemens	400 WMLxy400RJFS where (x=1-2) (y=1-2)	1	Ov/Un	1	4/5	Y	3,3a
Siemens	600 WMK13600RJ FPL Only	1/3	Under	1	7	Y	5
Square D	100 RC3042M100PS	1	Ov/Un	1	4/5	N	1,2
Square D	100 UTZ-6R1131C-FLSQD	1	Ov/Un	6	4	N	1
Square D	100 UTZ-xR1121C-FLSQD (x=2-5)	1	Ov/Un	2-5	4	N	1
Square D	125 EZMR11y125 (y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125 EZMR11y125CU (y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125 EZMR11y125X (y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125 EZMR31y125 (y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125 EZMR31y125CU (y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125 EZMR31y125X (y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125 MPYy125 (yy=22,33,44,55,66)	1	Ov/Un	2-6	5	N	1,2
Square D	125 QC816F125C	1	Ov/Un	1	4/5	N	1,2
Square D	125 UATZ-RS101C-FLSQD	1	Ov/Un	1	4	N	1 Al
Square D	125 UTZ-RS101C-FLSQD	1	Ov/Un	1	4	N	1
Square D	150 QC816F150C	1	Ov/Un	1	4/5	N	1,2
Square D	150 RC3042M150PS	1	Ov/Un	1	4/5	N	1,2
Square D	150 RC816F150C	1	Ov/Un	1	4/5	N	1,2
Square D	150 RQC150SFMG	1	Ov/Un	1	4/5	N	1,2
Square D	200 EZML11y200 (y=1-4)	1	Mtr Ctr	1-4	5	Y	1,2
Square D	200 EZML31y200 (y=2-4)	1	Mtr Ctr	2-4	5	Y	3a

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Square D	200 EZML33y200 (y=1-4)	3	Mtr Ctr	1	7	Y	4
Square D	200 EZMR11y200 (y=2-4)	1	Mtr Ctr	2-4	5	N	1,2
Square D	200 EZMR11y200CU (y=2-4)	1	Mtr Ctr	2	5	N	1,2
Square D	200 EZMR11y200X (y=2-4)	1	Mtr Ctr	2	5	N	1,2
Square D	200 MPLyy200 (yy=32,43,64)	1	Ov/Un	2-4	5	Y	3
Square D	200 MPR4y200 (y=2-3)	1	Ov/Un	2-3	5	N	1,2
Square D	200 MPR64200	1	Ov/Un	4	5	N	1,2
Square D	200 MPR8y200 (y=5-6)	1	Ov/Un	5-6	5	N	1,2
Square D	200 QC12L200C	1	Ov/Un	1	4/5	N	1,2
Square D	200 QC2442M200C	1	Ov/Un	1	4/5	Y/N	1,2
Square D	200 QC3040M200S	1	Ov/Un	1	4/5	N	1,2
Square D	200 QC816F200C	1	Ov/Un	1	4/5	N	1,2
Square D	200 RC12L200C	1	Ov/Un	1	4/5	N	1,2
Square D	200 RC200SFMG	1	Ov/Un	1	4/5	N	1,2
Square D	200 RC2040M200C	1	Ov/Un	1	4/5	N	1,2
Square D	200 RC2M200SFMG	1	Ov/Un	1	4/5	N	1,2
Square D	200 RC3042M200PS	1	Ov/Un	1	4/5	N	1,2
Square D	200 RC816F200C	1	Ov/Un	1	4/5	N	1,2
Square D	200 RQC200SFMG	1	Ov/Un	1	4/5	N	1,2
Square D	200 UAT-H4203x-FLSQD (x=B or T)	1	Over	1	4	Y	1 Al
Square D	200 UAT-H4213x-FLSQD (x=C or U)	1	Ov/Un	1	4	Y	1 Al
Square D	200 UAT-H5203x-FLSQD (x=B or T)	1	Over	1	5	Y	3,3a,b Al
Square D	200 UAT-H5213x-FLSQD (x=C or U)	1	Ov/Un	1	5	Y	3,3a,b Al
Square D	200 UAT-H7203x-FLSQD (x=B or T)	3	Over	1	7	Y	4 Al
Square D	200 UAT-H7213x-FLSQD (x=C or U)	3	Ov/Un	1	7	Y	4 Al
Square D	200 UAT-RS202B-FLSQD	1	Over	1	4	N	1 Al
Square D	200 UAT-RS212C-FLSQD	1	Ov/Un	1	4	N	1 Al
Square D	200 UAT-RS213A-FLSQD	1	Under	1	4	N	1 Al
Square D	200 UAT-RS213C-FLSQD	1	Ov/Un	1	4	N	1 Al
Square D	200 UAT-RS223A-FLSQD	1	Under	1	4	N	1 Al
Square D	200 UT-4R2352U-FLSQD	1	Ov/Un	4	4	N	1
Square D	200 UT92197CC-FLSQD	1	Ov/Un	1	4	N	1
Square D	200 UT-H4203x-FLSQD (x=B or T)	1	Over	1	4	Y	1
Square D	200 UT-H4213x-FLSQD (x=C or U)	1	Ov/Un	1	4	Y	1
Square D	200 UT-H5203x-FLSQD (x=B or T)	1	Over	1	5	Y	3,3a,b
Square D	200 UT-H5213x-FLSQD (x=C or U)	1	Ov/Un	1	5	Y	3,3a,b

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Square D	200 UT-H7203x-FLSQD (x=B or T)	3	Over	1	7	Y	4
Square D	200 UT-H7213x-FLSQD (x=C or U)	3	Ov/Un	1	7	Y	4
Square D	200 UT-RS202B-FLSQD	1	Over	1	4	N	1
Square D	200 UT-RS212C-FLSQD	1	Ov/Un	1	4	N	1
Square D	200 UT-RS213A-FLSQD	1	Under	1	4	N	1
Square D	200 UT-RS213C-FLSQD	1	Ov/Un	1	4	N	1
Square D	200 UT-RS223A-FLSQD	1	Under	1	4	N	1
Square D	200 UT-xR2332U-FLSQD (x=2-3)	1	Ov/Un	2-3	4	N	1
Square D	200 UT-xR2392UU-FLSQD (x=5-6)	1	Ov/Un	5-6	4	N	1
Square D	225 EZML11x225 (x=1-4)	1	Mtr Ctr	1-4	5	Y	1,2
Square D	225 EZML31x225 (x=2-4)	1	Mtr Ctr	2-4	5	Y	3a
Square D	225 EZML33x225 (x=1-4)	3	Mtr Ctr	1	7	Y	4
Square D	225 EZMR11x200X (x=2-4)	1	Mtr Ctr	2	5	N	1,2
Square D	225 EZMR11x225 (x=2-6)	1	Mtr Ctr	2-6	5	N	1,2
Square D	225 EZMR11x225CU (x=2-6)	1	Mtr Ctr	2-6	5	N	1,2
Square D	225 EZMR31x225 (x=2-6)	1	Mtr Ctr	2-6	5	N	1,2
Square D	400 1008836SQD	1	Ov/Un	1	4	Y	1
Square D	400 1008837SQD	1	Ov/Un	1	4	Y	1 Al
Square D	400 EZML31y400 (y=1-2)	1	Mtr Ctr	1-2	5	Y	3a
Square D	400 EZML33y400 (y=1-2)	3	Mtr Ctr	1-2	7	Y	4
Square D	400 QU12L400xL (x = C or S)	1	Under	1	4/5	Y	3
Square D	400 QU816D400SL	1	Under	1	4/5	Y	3
Square D	400 UAT-H4300T-FLSQD	1	Over	1	4	Y	1 Al
Square D	400 UAT-H5300T-FLSQD	1	Over	1	5	Y	3,3a,b Al
Square D	400 UAT-H5330U-FLSQD	1	Ov/Un	1	5	Y	3,3a,b Al
Square D	400 UAT-H7300T-FLSQD	3	Over	1	7	Y	4 Al
Square D	400 UAT-H7330U-FLSQD	3	Ov/Un	1	7	Y	4 Al
Square D	400 UT-H4300T-FLSQD	1	Over	1	4	Y	1
Square D	400 UT-H5300T-FLSQD	1	Over	1	5	Y	3,3a,b
Square D	400 UT-H5330U-FLSQD	1	Ov/Un	1	5	Y	3,3a,b
Square D	400 UT-H7300T-FLSQD	3	Over	1	7	Y	4
Square D	400 UT-H7330U-FLSQD	3	Ov/Un	1	7	Y	4
Talon	100 MP04061100R	1	Under	1	4	N	1
Talon	100 MP04061100R2	1	Under	2	4	N	1
Talon	100 MPS0406B1100R	1	Under	1	4	N	1
Talon	100 MPS0406B1100R2	1	Under	2	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Talon	100 UAB111-XG	1	Ov/Un	1	4	N	1
Talon	100 UAX411-XGF (X=2-6)	1	Ov/Un	2-6	4	N	1
Talon	125 49205-025F	1	Over	1	5	Y	3a
Talon	125 49207-025F	3	Over	1	7	Y	4
Talon	125 49305-025F	1	Over	1	5	Y	3a
Talon	125 49307-025F	3	Over	1	7	Y	4
Talon	125 MP0406B1125R	1	Under	1	4	N	1
Talon	125 MP0406B1125R2	1	Under	2	4	N	1
Talon	125 MPS0406B1125R	1	Under	1	4	N	1
Talon	125 MPS0406B1125R2	1	Under	2	4	N	1
Talon	125 TLxxRT (x=brkr/recpt config.)	1	Over	1,2	4/5	N	1,2
Talon	125 TLxxxRC (x=brkr/recpt config)	1	Under	1	4/5	N	1,2
Talon	125 TLxxxRM (x=brkr/recpt config.)	1	Un-Ped	1,2	4/5	N	1,2
Talon	125 TLxxxRP-F (x=brkr/recpt config.)	1	Un-Ped	1,2	4/5	N	1,2
Talon	125 WTG4x11RJ (X=4-6)	1	Ov/Un	5-6	5	N	2
Talon	125 WTG5411RJ	1	Ov/Un	4	5	N	2
Talon	125 WTG6x11RJ (X=5-6)	1	Ov/Un	5-6	5	N	2
Talon	125 WTGxx11RJ (X=2-4)	1	Ov/Un	2-4	5	N	2
Talon	135 UAT111-OGF	1	Ov/Un	1	4	N	1
Talon	135 UAT111-XGF	1	Ov/Un	1	4/5	N	1,2
Talon	135 UAT111-XMF	1	Ov/Un	1	5	N	2
Talon	135 UAT131-XGF	1	Ov/Un	1	4/5	N	1,2 AI
Talon	150 MP0406B1150R	1	Under	1	4	N	1
Talon	150 MP0406B1150R2	1	Under	2	4	N	1
Talon	150 MPS0406B1150R	1	Under	1	4	N	1
Talon	150 MPS0406B1150R2	1	Under	2	4	N	1
Talon	150 UAB417-150	1	Ov/Un	1	4/5	N	1,2
Talon	200 40005-01F	1	Over	1	5	Y	3,3a
Talon	200 40007-01F	3	Over	1	7	Y	4
Talon	200 40404-025F	1	Ov/Un	1	4	N	1
Talon	200 40405-015F	1	Ov/Un	1	5	Y	3,3a
Talon	200 40405-025F	1	Ov/Un	1	5	Y	3,3a
Talon	200 40405x-223F (x=2-6)	1	Ov/Un	2-6	5	Y	3a
Talon	200 40407-015F	3	Ov/Un	1	7	Y	4
Talon	200 40407-025F	3	Ov/Un	1	7	Y	4
Talon	200 40407x-223F (x=2-6)	3	Ov/Un	2-6	7	Y	4

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Talon	200 41005-01F	1	Over	1	5	Y	3,3a
Talon	200 41007-01F	3	Over	1	7	Y	4 Al
Talon	200 41405-025F	1	Ov/Un	1	5	Y	3,3a Al
Talon	200 41407-025F	3	Ov/Un	1	7	Y	4 Al
Talon	200 46705-025F	1	Ov/Un	1	5	Y	3a
Talon	200 46707-025F	3	Ov/Un	1	7	Y	4
Talon	200 46805-025F	1	Ov/Un	1	5	Y	3a
Talon	200 46807-025F	3	Ov/Un	1	7	Y	4
Talon	200 LG0408B1200RT	1	Ov/Un	1	4	N	1
Talon	200 LG0606L1200R or RA	1	Ov/Un	1	4/5	N	1, 2 Al
Talon	200 LG0816B1200RCT	1	Ov/Un	1	4	N	1
Talon	200 MP0406B1200R	1	Under	1	4	N	1
Talon	200 MP0406B1200R2	1	Under	2	4	N	1
Talon	200 MP0406L1200R	1	Under	1	4	N	1
Talon	200 MP0406L1200R2	1	Under	2	4	N	1
Talon	200 MPS0406B1200R	1	Under	1	4	N	1
Talon	200 MPS0406B1200R2	1	Under	2	4	N	1
Talon	200 UA27x6-ZGF (x=1 or 3)	1	Ov/Un	2	4	N	1 Al
Talon	200 UA37x7-ZGF (x=1 or 3)	1	Ov/Un	3	4	N	1 Al
Talon	200 UA47x9-ZGF (x=1 or 3)	1	Ov/Un	4	4	N	1 Al
Talon	200 UA57x9-MGF (x=1 or 3)	1	Ov/Un	5	4	N	1 Al
Talon	200 UA67x9-MGF (x=1 or 3)	1	Ov/Un	6	4	N	1 Al
Talon	200 UAB417-200	1	Ov/Un	1	4/5	N	1,2
Talon	200 UAB417-XPG	1	Ov/Un	1	4	N	1
Talon	200 UAS877-PGF	1	Under	1	4	N	1
Talon	200 UAT317-OGF	1	Over	1	4/5	N	1,2
Talon	200 UAT337-OGF	1	Over	1	4/5	N	1,2 Al
Talon	200 UAT417-PGF	1	Under	1	4/5	N	1,2
Talon	200 UAT417-XGF	1	Ov/Un	1	4/5	N	1,2
Talon	200 UAT417-XMF	1	Ov/Un	1	5	N	1,2 AL
Talon	200 UAT437-PGF	1	Under	1	4/5	N	1,2 Al
Talon	200 UAT437-XGF	1	Ov/Un	1	4/5	N	1,2 Al
Talon	200 UAT777-XGF	1	Ov/Un	1	4	N	1
Talon	200 UAx711-ZGF (x=2-4)	1	Ov/Un	2-4	4	N	1
Talon	200 UAx715-MGF (x=5-6)	1	Ov/Un	5-6	4	N	1
Talon	200 UAx71y-ZGF (x=2-4) (y=4-5)	1	Ov/Un	2-4	4	N	1

FPL - Florida Power and Light, DUKE Energy, OGE - Oklahoma Gas and Electric, TECO - Tampa Electric, GULF - Gulf Power



Participants: DUKE, FPL, GULF, OGE, TECO

Approved Metering Equipment Enclosure List

Revised
3/1/2019

**** Denotes new addition to this revision**

Manufacturer	Amps Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Talon	225 WTG10612RJ	1	Ov/Un	6	5	N	2
Talon	225 WTG4x12RJ (X=2-4)	1	Ov/Un	2-4	5	N	2
Talon	225 WTG6x12RJ (X=4-6)	1	Ov/Un	4-6	5	N	2
Talon	225 WTG8612RJ	1	Ov/Un	6	5	N	2
Talon	225 WTGL10612RJ	1	Ov/Un	6	5	Y	3a
Talon	225 WTGL4x12RJ (x=2-4)	1	Ov/Un	2-4	5	Y	3a
Talon	225 WTGL6x12RJ (x=4-6)	1	Ov/Un	4-6	5	Y	3a
Talon	225 WTGL8612RJ	1	Ov/Un	6	5	Y	3a
Talon	400 40905-02FL	1	Ov/Un	1	5	Y	3a
Talon	400 41105-02FL	1	Ov/Un	1	4/5	Y	3,3a Al
Talon	400 44707-02FL	3	Ov/Un	1	7	Y	4
Talon	400 46905-02FL	1	Ov/Un	1	5	Y	3a
Talon	400 47005-02FL	1	Ov/Un	1	5	Y	3a
Talon	400 47205-02FL	1	Ov/Un	1	5	Y	3a
Talon	400 47205-82FL	1	Ov/Un	1	5	Y	3a
Talon	400 47305-02FL	1	Ov/Un	1	5	Y	3a
Talon	400 47305-82FL	1	Ov/Un	1	5	Y	3a
Talon	400 47407-02FL	3	Under	1	7	Y	4
Talon	400 47504-92	3	Under	1	4	Y	3
Talon	400 47604-82	3	Ov/Un	1	4/5	Y	3,3a
Talon	400 47705-02FL	1	Ov/Un	1	4/5	Y	3,3a
Talon	400 49005-02FL	1	Ov/Un	1	4/5	Y	3,3a
Talon	400 49007-02FL	3	Ov/Un	1	7	Y	4
Talon	400 49105-02FL	1	Ov/Un	1	4/5	Y	3,3a Al
Talon	400 49107-02FL	3	Ov/Un	1	7	Y	4 Al
Talon	400 UAT-131-xgf	1	Over	1	4	Y	1 Al
Talon	600 9817-9526 (Requires Ridged Lugs) FPL ONLY	1,3	Ov/Un	1	7	Y	5
Talon	600 9817-9527 (Requires Ridged Lugs) FPL ONLY	1,3	Ov/Un	1	7	Y	5 Al